

## SOCK 86218



SOCK\_86218\_4f6b0c9238dc1.jpg

FAGOR BSD 201 S

Manufacturer: [Fagor](#)

### Description

Number of outputs: 2  
Band coverage: 5-2300MHz  
DC pass IN-OUT 300 mA max: No  
DC pass SAT 300 mA max: No

Through losses  
5 - 30 MHz: SINGLE\*  
47 - 862 MHz: SINGLE\*  
950 - 2150 MHz: SINGLE\*  
2150 - 2300 MHz: SINGLE\*

\*must be connected directly to tap-offs or splitter.

Derivation losses  
5 - 30 MHz: 0,5dB  
47 - 862 MHz: 1dB  
950 - 2150 MHz: 1dB  
2150 - 2300 MHz: 1dB

Directivity  
5 - 30 MHz: --  
47 - 862 MHz: --  
950 - 2150 MHz: --  
2150 - 2300 MHz: --

Isolation TV-R  
5 - 30 MHz: 30dB

47 - 862 MHz: 15dB  
950 - 2150 MHz: 15dB  
2150 - 2300 MHz: 18dB

Return losses  
5 - 862 MHz: 10dB  
950 - 2300 MHz: 6dB

Shielding factor  
VHF 30 - 300 MHz: 75dB  
UHF 300 - 862 MHz: 65dB  
SAT 950 - 2300 MHz: 55dB