

MSW 4476ST



MSW_4476ST_4f6991cc13aeb.jpg

9X9X6 CASCAD.MULTISWITCH

Manufacturer: [JESMAY](#)

Description

- 8 satellite IF inputs and 1 terrestrial TV input
- 9 Outputs + 6 TAPS
- 8 satellite IF inputs meet complex SMATV system requirement
- Tap outputs select trunk signal by 13/18V, 22kHz and DiSEqC 2.0 commands
- Support network remotely power via trunk ports
- Sheet metal housing with plastic holder
- Frequency Range: 47-862 / 950-2150
- Return path: 5-30MHz
- Trunk Loss Sat: 4dB / Terr: 5dB
- Tap Loss Sat: 3dB / Terr: 5dB / Return: 24dB
- Switching Isolation: 25dB
- Isolation: 30dB
- Return Loss: Trunk:10dB / Tap:8dB
- SAT Output Level: 100@35dB IMA3 EN50083-3
- Terr Output Level: 88@35dB IMA3 EN50083-5
- DC Current Consumption: 25mA
- Max Current Pass Per Trunk: 500mA
- Dimensions: 254x128x49 mm