

SOCK 86277



BRF 05N

Manufacturer: [Fagor](#)

Description

GB		BRF			
MODEL		BRF 11 S	BRF 01 S	BRF 01 N	BRF 05 N
Reference		86274	86275	86276	86277
Technology		Inductive / Inductive			
Bande coverage		5 ± 1250		5 ± 1000	
Through loss		Inductif Single"		Final End	2,5
TV		0,5		2,5	2,5
R		0,5		3	7
Derivation loss		0,5		0	12,5
TV		—		—	—
R		—		—	—
Directivity		—		—	—
TV - R		30		—	—
Isolation		—		—	—
TV - R		—		—	—
Shielding factor		175		145	—
TV - R		—		—	—
Impedance		75		—	—
Return loss		—		—	—
TV		—		—	—
Output connector		—		—	—
TV		—		—	—
Packing dimensions (20 u)		—		—	—
Weight (20 u)		—		—	—